

# 5HZ6

## Sharp-Cutoff Pentode With Two Independent Control Grids

### Controlled Heater Warm-up Time

*The 5HZ6 is the same as the 6HZ6 except for:*

#### Heater Characteristics and Ratings

Current . . . . .	0.600 ± 0.040	A
Voltage (ac or dc) at 0.600 A . . . . .	4.75	V

# 5J6

## Medium-Mu Twin Triode

### Controlled Heater Warm-up Time

*The 5J6 is the same as the 6J6A except for:*

#### Heater Characteristics and Ratings

Current . . . . .	0.600 ± 0.040	A
Voltage (ac or dc) at 0.600 A . . . . .	4.7	V

# 5KE8

## Medium-Mu Triode— Sharp-Cutoff Pentode

*The 5KE8 is the same as the 6KE8 except for:*

#### Heater Characteristics and Ratings

Current . . . . .	0.450 ± 0.030	A
Voltage (ac or dc) at 0.450 A . . . . .	5.6	V
Warm-up Time (Average) . . . . .	11	s

# 5MQ8

## Medium-Mu Triode— Sharp-Cutoff Pentode

*The 5MQ8 is the same as the 6MQ8 except for:*

#### Heater Characteristics and Ratings

Current . . . . .	0.600 ± 0.040	A
Voltage (ac or dc) at 0.600 A . . . . .	5.6	V
Warm-up Time (Average) . . . . .	11	s